



**Fixture Specifications**

Fixture	Part Number	Lamps	Lamp Type	Dimensions	Weight w/Lamps
8ft Mega Double	CFX-9602	2	F120 / T12	97 x 7.5 x 3.5" w/ 3.5" barndoors (246.5 x 33 x 9cm w/ 9cm barndoors)	10 lb (4.5kg)
6ft Mega Double	CFX-7202	2	F100 / T12	73.5 x 7.5 x 3.5" w/ 3.5" barndoors (186.5 x 19 x 9cm w/ 9cm barndoors)	9.2 lb (4.1kg)

**Ballast Specifications**

Ballast	Part Number	Input Voltage	Output Frequency	Amperage	Lamp Switching	Output Switching	Dimensions	Weight
Mega Double	BAL-227M-120U	100~240VAC	25kHz	F120/2.2A, F100/1.7A	1~2	HO/Std	8.8 x 9.3 x 2.7" (22 x 24 x 7cm)	3.4 lb (1.5kg)
Mega Double	BAL-227M-230U	240~100VAC	25kHz	F120/1.1A, F100/0.9A	1~2	HO/Std	8.8 x 9.3 x 2.7" (22 x 24 x 7cm)	3.4 lb (1.5kg)

**▼ Photometrics**

<b>8ft Double</b>	FC	314	132	73	45	30	22	16.5	13	10.5	8.5
	Feet	2	4	6	8	10	12	14	16	18	20
<b>6ft Double</b>	FC	292	111	55	33	22	16	12	9	7	6
	Feet	2	4	6	8	10	12	14	16	18	20

<b>8ft Double</b>	LUX	4166	1906	1055	678	458	331	254	200	163	131
	Meters	0.5	1	1.5	2	2.5	3	3.5	4	4.5	5
<b>6ft Double</b>	LUX	3983	1597	829	506	337	241	182	142	114	92
	Meters	0.5	1	1.5	2	2.5	3	3.5	4	4.5	5